


# Solar Flood Light 10W, 4000K MORRIS# 72535








#### **Features:**

- High sensitivity PIR sensor Switch
- 20 Hour Charge Time
- 7-10 Day Run Time
- Includes Battery Heater for Cold Weather Applications
- Charging Temperature: 32°F -104°F
  Discharging Temperature: -4°F-140°F

- High Lumen Output LEDs
- Power Source: Epoxy Mono-Crystalline Solar Panel - .5W
- IP65 Wet Location Rated
- Easy Installation
- 2 Year Warranty

Part#	ССТ	Lumens	Light Pattern	Dimming
72535	4000K	F,000	1H0°	N/A

**PHOTOMETRY** 



www.morrisproducts.com



# Solar Flood Light 10W, 4000K MORRIS# 72535

#### **Technical Specifications:**

**Electrical:** 

Power: Epoxy Mono-Crystalline, .5W

**Product Parameters:** 

Wattage: 10W

CCT: 4000K (Cool White)

**Sensor Parameters:** 

Beam Angle: 130°

Sensing Distance: 20'

**Component Specifications:** 

LED: SMD 2835

Comes with Li-ion Battery

Capacity: 3.7V 7.4WH 2AH/PC Charging/

Discharging Temp: 32°F -104°F/ -4°

F-140°F

Charging Time: 15 hours

Ra 80+

Non-Dimmable

Operating Temperature: -4°F-140°F

Charging Temperature: 32°F -104°F

Discharging Temperature: -4°F-140°F

**Construction:** 

Housing: Aluminum

**Powder Coated** 

IP Rating: IP65 Wet Location Rated

Mounting: Wall Mount/Post Mount

Carton Qty: 1

Warranty:

Morris Products carries a 2 year warranty from date of purchase against defects in materials and workmanship (assuming normal

and proper usage).

Morris CAT#: 72535 - Installation Instructions

### **Installation Instructions:**

- 1. When installing this fixture to a concrete wall, use a 1/4" drill bit and create two guiding holes on the wall surface.
- 2. Gently hammer the plugs (included) into the holes and use the screws to secure the fixture to the wall.
- 3. When installing this fixture on a wooden wall or surface, use a 1/8" drill bit to create guiding holes in the wall. Using the screws provided, secure the fixture to the wooden wall/surface. The plastic plugs are not required.

**NOTE:** Use the cable ties (included) to mount this fixture to railings or a post. Be sure the Solar Panel is facing upward.

\_\_\_\_1 \_\_\_\_

Morris CAT#: 72535 - Installation Instructions

## **Operating Instructions:**

- To turn on this fixture, press the white button on the front of the light for 3 seconds.
- 2. To toggle between lighting modes, press the white button.
- 3. A green light will flash once, twice or three times which indicates the lighting mode currently selected:

**Mode 1 (One Flash)**: The fixture is off during inactivity.

Mode 2 (Two Flashes): 20 lumen brightness during inactivity.

Mode 3 (Three Flashes): 20 lumen brightness at all times. The motion sensor is disabled.

4. To turn off the fixture, press and hold the white button for 3 seconds.

**NOTE:** The Solar Panel on this fixture acts as a photocell. This product only comes on when light levels are low.

2	

#### Morris CAT#: 72535 - Installation Instructions



### **NOTE:**

 Do not install this fixture in an area that doesn't receive direct sunlight.



## **WARNING:**

- Keep this fixture away from any fire, oil or dangerous chemicals.
- This fixture should be installed by a qualified electrician only, following all national and local electrical code regulations.
- Disassembling or tampering with this fixture will void the warranty.
- If this fixture doesn't get a sufficient charge for 7 days or more, try charging the fixture in an area with stronger & brighter sunlight.
- To ensure this fixture continues to function properly, please clean the solar panel every 6 months or more frequently if the install area requires it.

3	