



# ESB432-14

## APPLICATION and PERFORMANCE SPECIFICATION

Electronic ballast for 4, 3, 2 and 1 T12HO lamps up to 8ft long or any combination thereof from 4-32 ft. Electronic ballast for 4, 3, 2 and 1 T8HO lamps up to 6ft long or any combination thereof from 4-24 ft. Electronic ballast for use with T12HO/T8HO lamps or any combination of lamps in circuit as long as total length per circuit does not exceed 7ft for T12HO/5ft for T8HO.

• Line Voltage: 120 - 277 vac, ±10%, 50/60Hz

• Parallel Lamp Operation

Instant Start

Active Power Factor Correction

\*60 Hz data

Lamp		Lamp Footage		Volts	Max Input Power	Nominal Line Current	Power	Harmonic	Crest
Type	#	Min	Max		(Watts)	(Amps)	Factor	Total	Factor
T12HO	4,3,2,1	4	32	120	282	2.35	>.90	<10%	<1.7
T12HO	4,3,2,1	4	32	277	275	1.03	>.90	<10%	<1.7
T8HO	4,3,2,1	4	24	120	257	2.14	>.90	<10%	<1.7
T8HO	4,3,2,1	4	24	277	250	0.90	>.90	<10%	<1.7

Application and Performance Specification Information Subject to Change without Notification.

Power factor >.85 for 4-5ft applications, THD <20% for 4-12ft applications

## Performance:

- Meets ANSI Standard C82.11-1993
- Meets FCC Part 18 (Class A) for EMI and RFI Non-Consumer Limits

## Application:

Minimum Starting Temperature:
 Maximum Case Temperature:
 Sound Rated:
 -20° F, -29° C
 176° F, 80° C
 A

## Safety:

- No PCB's
- $_{\text{C}}\text{UL}_{\text{US}}$  Listed

(Class P, Type HL, Type 2 Outdoor)

CSA Listed

## **Physical Parameters:**


Length: 14.31"
Width: 3.24"
Height: 2.67"
Weight: 7.4 lbs
Carton Quantity: 1 piece

• Lead length: Black, White  $24" (\pm 1")$ Red, Blue  $120" (\pm 1")$ 


#### Warranty:

Universal Lighting Technologies warrants to the purchaser that each electronic ballast will be free from defects in materialor workmanship for a period of 4 years from date of manufacture when properly installed and under normal conditions of use. Call **1-800-BALLASTx800** for technical assistance.

## Manufactured in North America



**Multiple Lamp Application** 



For 3-lamp, 2-lamp and 1-lamp application individually cap red and blue leads