

35W Bright White (3000K) GY6.35 Base (T4 Replacement) Dimmable Clear Quartz Halogen Light Bulb

Features

- Fits a variety of residential and commercial lighting applications
- Dimmable light
- Halogen technology is more energy efficient and longer lasting than traditional incandescent lighting
- **Ideal usage:** General purpose lighting



Specifications

Item Number	Item Length (In)	Item Width (In)	Bulb Shape
BPQ35T4/JCD-	1.8	0.5	T4
Bulb Type	Bulb Base	Bulb Finish	Technology
Tubular	GY6.35	Clear	HALOGEN
Brightness (LUMENS)	Lumen Efficiency (LPW)	Beam Angle	Color Accuracy (CRI)
400	11.43	360	99
Color Temperature (CCT)	Life Hours	Life Years	Voltage (V)
3000	2000	1.8	120
Annual Energy Cost (\$)	Energy Used (Wattage)	Battery Operated	Pack Quantity
4.22	35	No	1
Smart	Portable	Dimmable	Hardwire
No	No	Yes	No
Enclosed Fixture Rated	CEC Compliant		
Yes	Not Regulated		