

CST1 | Commercial Strip

HIGHLIGHTS

- Performance commercial strip designed with value in mind
- Unique push button access allows for the lens and LED board to be easily removed, allowing quick access to driver
- Easily add a behind the lens standalone control solution; minimal wiring required
- Available in 4' and 8' lengths
- 2 x 1/2" knockouts on each end
- Linear alignment plate accessory makes row mounting quick and easy (surface and suspension alignment plates available)
- V-Hooks included with fixture

CERTIFICATIONS

- ETL listed for US & Canada
- **RoHS Compliant**
- FCC Compliant
- ICES-005 Compliant
- Damp Location rated
- DLC Listed

PERFORMANCE

- High efficacy, up to 130 lm/W
- Available in fixed wattage models: 32W, 64W Available in single CCT models: 4000K or 5000K
- CRI: >80
- Beam Angle: 120°
- Rated Life L70: >54,000 Hours

ELECTRICAL

- Input voltage: 120-277V
- 0-10V dimming, dim-to-off
- 12VDC Aux, 200mA
- Surge Protection: 2kV
- Power Factor: >0.9
- THD: <20%

THERMAL

- -4°F to 113°F (-20°C to 45°C) ambient operating temperature
- Ambient operating temperature with sensor (see selected sensor datasheet)

CONSTRUCTION

- White powder coated steel housing
- Diffused polycarbonate lens

WARRANTY

* 5 Year limited warranty available online. Contact your EiKO sales rep for additional details.

| project name | type |
|----------------|---------|
| catalog number | voltage |
| approved by | date |



















APPLICATIONS

- Warehouses
- Manufacturing Plants
- Distribution Centers
- **Grocery Stores**
- Indoor Recreational Facilities
- Big Box Retail
- Service Repair Centers

KEY FEATURES

PUSH BUTTON RELEASE

Push buttons located on the side allow for the lens and LED board to be quickly removed, making wiring and installation easier

ALIGNMENT PLATE ACCESSORY

Optional alignment plate accessory available to make row mounting connections easy (available for both surface and suspension mounting)

MOUNTING OPTIONS

V-Hooks included for suspension-ready installation right out of the box. Optional aircraft cable accessory available, compatible with suspended alignment plate

BEHIND THE LENS SENSOR READY

Simply snap-in the behend the lens sensor and make electrical connection using wire nuts provided.





INCLUDED V-HOOKS FOR SUSPENSION INSTALLATIONS



ALIGNMENT PLATE ACCESSORY FOR SURFACE AND SUSPENDED ROW MOUNTING



eiko.com

AVAILABLE MODELS

| ORDER | ORDER ORDER | ITEM # | LENGTH | WATTS | ССТ | LUMENS | EFFICACY (Im/W) | VOLTAGE | TRADITIONAL WATTAGE EQUIVALENT | DLC |
|-------|-------------|---------------|--------|-------|-------|---------|--------------------|----------|-----------------------------------|----------|
| URDER | CODE | 112W # | LENGIH | WAITS | | | | | | STANDARD |
| | 13412 | CST1-432-40-U | 4′ | 32W | 4000K | 4160 lm | 130lm/W | 120-227V | 2 lamp 32W T8 | S-6FNU4R |
| | 13413 | CST1-432-50-U | 4′ | 32W | 5000K | 4160 lm | 130lm/W | 120-227V | 2 lamp 32W T8 | S-DW40FA |
| | 13414 | CST1-864-40-U | 8′ | 64W | 4000K | 8320 lm | 130lm/W | 120-227V | 2 lamp 96W T8 / 4 lamp 32W T8 | S-CF5Y2M |
| | 13415 | CST1-864-50-U | 8′ | 64W | 5000K | 8320 lm | 130lm/W | 120-227V | 2 lamp 96W T8 / 4 lamp 32W T8 | S-8KA9Q2 |

| FACTORY INSTALLED OPTIONS | | | | | | | |
|---|--|--|--|--|--|--|--|
| CUSTOM CORD LENGTH | CORD END | | | | | | |
| [Blank]: Default, no cord W1xx: 300V 18/3 white cord W3xx: 600V 18/6 white cord with dimming wires and a 24/7 hot wire for battery backup (Cord end option is not available) Custom length required (in feet) | [Blank]: Default, no cord end N01: 125V 15A straight plug N02: 250V 15A straight plug N04: 125V 15A locking plug N05: 250V 15A locking plug N06: 277V 15A locking plug N07: 125V 20A straight plug N08: 250V 20A straight plug N09: 277V 20A straight plug N10: 125V 20A locking plug N11: 250V 20A locking plug N11: 250V 20A locking plug N11: 250V 20A locking plug | | | | | | |

| | MODEL CONFIGURATOR | | | | | | | | FACT | DRY | INSTALLED OPTIONS | |
|-------|--------------------|------|---|-------|---|-----|---|---------|------|-------------|-------------------|----------|
| MODEL | - | SIZE | - | WATTS | - | ССТ | - | VOLTAGE | - | CORD LENGTH | - | CORD END |
| CST1 | - | | - | | - | | - | | - | | - | |

EXAMPLE PART NUMBER: CST1-432-40-U-W130-M08

REFER TO FOLLOWING SECTIONS FOR DETAILS ON FACTORY INSTALLED OPTIONS & AVAILABLE FIELD INSTALLED OPTIONS

ACCESSORIES

| ORDER | ORDER CODE | ITEM # | DESCRIPTION | |
|-------|---------------|------------|--|----------|
| | 14341 | CST1-SM-AP | CST1 4/8ft Surface Mount Alignment Plate | |
| | 13520 | CST1-SA | CST1 4ft Suspension Aircraft Cable, Order x2 for 8ft | |
| | 13519 | CST1-SA-AP | CST1 4/8ft Suspended Mount Alignment Plate | u parti. |

BATTERY BACKUPS

| ORDER | ORDER CODE | ITEM # | DESCRIPTION |
|-------|---------------|--------------|---|
| | 10918 | EEBN08WUA050 | EiKO Emergency Battery Kit Internal 8W 120-277VAC 25-50VDC CEC Compliant. Field Installed Only. |
| | 10896 | EEBN15WUA050 | EiKO Emergency Battery Kit Internal 15W 120-277VAC 25-50VDC CEC Compliant. Field Installed Only |
| | 10897 | EEBN20WUA050 | EiKO Emergency Battery Kit Internal 20W 120-277VAC 25-50VDC CEC Compliant. Field Installed Only. |



CONTROLS & SENSORS

| ORDER | ORDER CODE | ITEM # | DESCRIPTION |
|---------|---------------|---------------|--|
| STANDA | LONE CON | TROLS | |
| PIR SEN | SORS | | |
| | 800654 | MS2-OPD-3 | Stand-alone PIR Motion Sensor, 120-347V, 1/2" knock-out, On/Off, Ambient Threshold, 40ft, Parameters set by dip switch Order separately. |
| | 800655 | MS2-DPX-3 | Stand-alone PIR Motion Sensor, 120-347V, 1/2" knock-out, 0-10V, Ambient Threshold, 40ft, Parameters set by dip switch or RC-100/SEN5A-ACT Order separately. |
| | 10220 | SEN-3B-KO | Stand-alone PIR Motion Sensor, 120-277V, IP66, 1/2" knock-out, 0-10V, Ambient Threshold, 30ft, Parameters set by SEN-3-RC. |
| | 10476 | SEN-3AA-KO | Stand-alone PIR Motion Sensor, 120-277V, 1/2" knock-out, On/Off, Ambient Threshold, 30ft, Parameters set by dip switch. |
| | 13342 | SEN5A-SZPR-WH | Stand-alone PIR Motion Sensor, 12-24V, Z10, 0-10V, Daylight Harvesting, 40ft, White, Parameters set by SEN5A-ACT. Note: Note: Swivel mount adapter required: SENA-AZ-WH |
| MICROW | AVE SENS | ORS* | |
| | 313895 | MS1-DHR-KO-1 | Stand-alone Microwave Motion Sensor, 120-277V, IP65, 1/2" knock-out, 0-10V, Ambient Threshold, 48ft, Parameters set by RC01. Note: Swivel mount adaptor required: SENA-AZ-WH. |
| | 12150 | SEN/M/S1C/KO | Stand-alone Microwave Motion Sensor, 120-277V, IP65 1/2" knock-out, 0-10V, Ambient Threshold, Parameters set by SEN-S1-RC3. |
| | 13341 | SEN5A-SZMR-WH | Stand-alone Microwave Motion Sensor, 12-24V, Z10, 0-10V, Daylight Harvesting, 40ft, White, Parameters set by SEN5A-ACT. Note: Swivel mount adapter required: SENA-AZ-WH. |
| | 11931 | SEN5A/M/Z10 | Stand-alone Microwave Motion Sensor, 12-24V, Z10, 0-10V, Ambient Threshold, 40ft, Parameters set by RC-100/SEN5A-ACT. Note: Swivel mount adapter required: SENA-AZ-WH. |
| | 13696 | SENA-SHMR | Stand-alone Microwave Motion Sensor, 12-14V, Behind the lens Snap-in, 0-10V, Daylight Harvesting, 8-20ft, 16" wires, Parameters set by SEN5A-ACT. |

^{*} Microwave sensors must be installed on stable and immovable fixtures to avoid false activation from swinging.

| REMOTE | REMOTES FOR COMMISSIONING STANDALONE CONTROLS | | | | | | |
|--------|---|------------|---|--|--|--|--|
| | 13344 | SEN5A-ACT | Commissioning Tool for SEN5A, BAY-E-SEN/PIR, BAY-E-SEN/M, and MS2-DPX-3 (Backward compatible with SEN5A/CT and RC-100). | | | | |
| | 10226 | SEN-3-RC | Commissioning Tool for SEN-3B-KO and SEN-3C-KO. | | | | |
| | 313897 | RC01 | Commissioning Tool for MS1-DHR-SA-4, MS1-DHR-KO-1, MS1-DHR-KO-4. | | | | |
| | 10917 | SEN-S1-RC3 | Commissioning Tool for SEN/M/S1C/KO. | | | | |

| NETWO | NETWORKED LIGHTING CONTROLS (NLC) | | | | | | |
|-----------------------|-----------------------------------|------------------------|--|--|--|--|--|
| SENSOR AND CONTROLLER | | | | | | | |
| | 13246 | SENA-WZPA-WH | BLE PIR Motion sensor, 12-24V,IP65, Z10, 0-10V, Daylight Harvesting, 40ft, Parameters set by Silvair App. Note: Swivel mount adapter required: SENA-AZ-WH | | | | |
| | 12643 | PSC-ZKV-WCM-100-BLE-SR | BLE TruBle wireless fixture Controller, 12-24V, Z10, 0-10V, Parameters set by Silvair App. Note: Swivel mount adapter required: SENA-AZ-WH | | | | |

| WALLOF | WALL OR WIRELESS CONTROLLERS | | | | | | | |
|--------|------------------------------|------------------------|--|--|--|--|--|--|
| | 12654 | ESRPB-W-EO | BLE Easyfit by EnOcean wireless self-powered kinetic Single rocker pad, white, wall plate included. | | | | | |
| | 12655 | EDRPB-W-EO | BLE Easyfit by EnOcean wireless self-powered kinetic Double rocker pad, white, wall plate included. | | | | | |
| | 12635 | PSC-DM-WS-100-BLE-SR | BLE TruBlu 120-277V, Single Gang Single Button Wall Controller, White, Parameters set by Silvair App. | | | | | |
| | 12636 | PSC-DM-I-WS-100-BLE-SR | BLE TruBlu PIR Occupancy/ Vacancy Sensor, 120-277V, Single Gang Wall Controller, White, Parameters set by Silvair App. | | | | | |
| | 12637 | PSC-DM-WS-400-BLE-SR | BLE TruBlu 120-277V, Single Gang 4-Button Wall Controller, White, Parameters set by Silvair App. | | | | | |
| ADAPTE | ADAPTERS & ACCESSORIES | | | | | | | |
| | 13343 | SENA-AZ-WH | Z10 White Stem Swivel Mount bracket 12-24VDC Max. 22AWG 2ft V+(1:Yellow) Dim-(2:Pink) Dim+(3:Purple) Optional(4:Brown) | | | | | |



PRODUCT DIMENSIONS



96*/2438mm

8' MODELS

2.7"/69mm