# T<sub>6</sub>C

## 2x4 LED Troffer

# **Product Description**

Designed for easy contractor installation, the T6C LED Troffer features a pre-mounted driver and a maintenance-free, fully-sealed chamber with seamless Aluminum frame to keep bugs and dust out. The fixture utilizes a precision-engineered, textured diffuser to deliver maximum lumen output and optimal uniformity without revealing hot spots or shadowing. The T6C LED Troffer fits easily into standard ceiling grids and is available in 1x4, 2x2, and 2x4 configurations, making it ideal for new construction and retrofit projects.

#### Construction

- Extruded aluminum frame with powder coat finish
- Durable stamped housing
- High efficiency, fully sealed, maintenance-free LED chamber
- Smooth formed sides for safe handling

#### **Optical System**

- Patented internal optical system
- Precision engineered polystyrene diffuser
- · High reflectivity internal coating
- No visible diodes, hot-spots, or shadows providing high uniformity, and reduced glare

### **Electrical**

- Input voltage of 120-277VAC
- Full-range dimming via 0-10VDC controls
- 4kV surge protection standard
- TM-21 Reported L70(10k) life >54,000 hours
- LM-79, LM-80 testing performed in accordance with IESNA standards
- Meets FCC 15 PartB: 2016 Class A requirements

#### Mounting and installation

- Features a pre-mounted driver for contractor friendly installation
- Single cover plate with access to both line and low voltage connections.
- Can be installed in conventional suspended grid ceiling or drywall with an optional adaptor
- Integral grid tie clips with wire holes provided for seismic requirements
- · Certified for direct contact with insulation
- $\bullet$  Operating temperature rating of -4°F to 104°F (-20°C to 40°C)
- For installations where power surge may be possible, NICOR recommends installing additional surge protection at the fixture or electrical distribution panel

### Finish

Gloss white

### **Options**

- High Voltage (347-480VAC) option
- Drywall adaptor/flange kit (FK24)
- Surface mount kit (SK24) converts T6C Series troffers into surface mount luminaires
- Emergency battery backup kit

## Warranty


- 5-year limited system warranty standard
- Warranty does not cover product failure due to an overvoltage event (power surge.)

Project

Catalog

Type


















## **Photometric Data**

# T6C24 3500K

Input Voltage (VAC)	120-277
System Level Power (W)	35.32
Delivered Lumens (Lm)	4426
System Efficacy (Lm/W)	125.3
Correlated Color Temp (K)	3461
Color Rendering Index (CRI)	83
Beam Angle	113°
Spacing Criteria	1.27



Intensity Summary (Candle Power)		
Angle	Mean CP	
0	1516	
10	1491	
20	1414	
30	1288	
40	1119	
50	913	
60	679	
70	428	
80	186	
90	0	

CCT Data Mu	ltiplier
T6C24SU40	1.007
T6C24SU50	1.012


Con	n	
Mounted height (Feet)	Footcandles Beam Center	Diameter (Feet)
8	24.0	24.2
10	15.3	30.2
12	10.6	36.3
14	7.8	42.3

Zoi	nal Lumen Summa	ry
Zone	Lumens	% of Luminaire
0-30	1192	26.9%
0-40	1956	44.2%
0-60	3467	78.3%
0-90	4426	100%
90-180	0	0%
0-180	4426	100%

Fixture tested per LM-79-08. Photometric data is of the performance of a representative fixture. Results may vary in the field.

# T6C24H 3500K

Input Voltage (VAC)	120-277
System Level Power (W)	46.50
Delivered Lumens (Lm)	5851
System Efficacy (Lm/W)	125.8
Correlated Color Temp (K)	3458
Color Rendering Index (CRI)	83
Beam Angle	113°
Spacing Criteria	1.28



Intensity Summary (Candle Power)		
Angle	Mean CP	
0	2025	
10	1993	
20	1891	
30	1728	
40	1505	
50	1231	
60	917	
70	579	
80	249	
90	3	

CCT Data Mult	iplier
T6C24HU40	1.017
T6C24HU50	1.018

Con	e of Light Tabulatio	n
Mounted height (Feet)	Footcandles Beam Center	Diameter (Feet)
8	31.6	24.2
10	20.2	30.3
12	14.1	36.3
14	10.3	42.4

	Zonal Lumen Summary		
Zone	Lumens	% of Luminaire	
0-30	1575	26.9%	
0-40	2584	44.2%	
0-60	4583	78.3%	
0-90	5851	100%	
90-180	0	0%	
0-180	5851	100%	

Fixture tested per LM-79-08. Photometric data is of the performance of a representative fixture. Results may vary in the field.

	Performance	Data	
Model Number	Lumens	Watts	Lumens/Watt
 T6C24SU35	4426	35.3	125.3
T6C24SU40	4455	35.3	126.2
T6C24SU50	4478	35.2	127.2
T6C24HU35	5851	46.5	125.8
T6C24HU40	5952	46.8	127.2
T6C24HU50	5954	46.8	127.2

Recommended Dimmers*	Accessories	Accessories sold separa
Lutron NTSTV	Accessories	Accessories sola separa
Lutron DVSTV	Surface Mount Kit	TPE10SK24
Cooper SF10P	Surface Mount Kit for use with EM	SK24
Legrand RH4FBL3PW	Drywall Frame Kit	FK24

\*Not a complete list. Check compatibility before installation.

Ordering Information					Example: T6C24SU40
Series	Size	Output	Voltage	CCT's	EM (Optional)
T6C	<b>24</b> (2 x 4)	<b>S</b> (Standard)	<b>U</b> (120-277V)	<b>35</b> (3500 K)	<b>E1</b> (EMB045)
		<b>H</b> (High Output)	<b>H</b> (347-480V)	<b>40</b> (4000 K)	<b>E2</b> (EMB080)
				<b>50</b> (5000 K)	<b>E3</b> (EMB250)

Specifications and dimensions subject to change without notice.

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

NOTE: This equipment has been tested and found to comply with the limits for a Class A digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference when the equipment is operated in a commercial environment. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instruction manual, may cause harmful interference to radio communications. Operation of this equipment in a residential area is likely to cause harmful interference in which case the user will be required to correct the interference at his own expense.



sold separately